
DENSO

FIXED TYPE 2D CODE SCANNER QB30 SERIES

Wide-field model QB30-SU QB30-SR Standard-range model QB31-SU QB31-SR



Two models available for a wide range of applications



On a plant line



As a kiosk terminal



For an entrance gate terminal



FIXED TYPE 2D CODE SCANNER

Scanning performance

Two models available, depending on the application

[QB30] Wide-field model with small footprint With its compact body and wide-angle lens, QB30 can be installed in a small space without needing to be a certain distance from the scanned object. It can reduce installation space when mounted on a kiosk terminal, allowing users to install it anywhere they wish.

* It is recommended to use a low-reflection coating plate in case you wish to install a plate on the scanning side

Full functions

Easy setup function adopted

"QB setting," which is a software application enabling users to easily set up scanning conditions and data formats according to the scanned objects, is provided free. It simplifies the troublesome setup process, reducing the user's burden at the time of introduction.

Internal environment performance

Safety function which blocks the intrusion of dirt and water drop

Materialized IP54, the protection rating of IEC. Shut out ingress of dust at the production line or rainwater at a semi-outdoor. It can be installed safely.



QB30 series specification

Туре			QB30-SR (RS-232C model)	QB30-SU (USB model)	QB31-SR (RS-232C model)	QB31-SU (USB model)
Scanner unit	Readable code	2D code	QR code, micro QR code, SQRC, iQR, PDF417, micro PDF417, Maxi code, DataMatrix(ECC200), Aztec, GS1 Composite(EAN.UCC Composite)			
		Barcode	EAN-13/-8(JAN-13/-8), UPC-A/-E, UPC/EAN(Add an add-on), Interleaved 2 of 5, CODABAR(NW-7), CODE39, CODE93, CODE128, GS1-128, GS 1 DataBar(RSS)			
	Minimum resolution	2D code	0.20mm		0.17mm	
		Barcode	0.15mm			
	Marker light		-		Visible semiconductor laser (red 1 mW max; JIS Class 2)	
	Scanning reference position		40mm		90mm	
	Scanning range ^{*1}		62mm x 39mm		56mm x 30mm	
	Label moving rate ^{*2}		800mm/s	-	500mm/s	-
	Lighting		White LED Red LED		LED	
	Confirm scan	LED	One (Blue, green, red)			
		Buzzer	3-step volume control, 3-step tone control			
Interface	Interface		RS-232C(Mini D-sub 15-pin female)*3	USB	RS-232C(Mini D-sub 15-pin female)*3	USB
	Cable length		0.5m	2m	0.5m	2m
External	Input		Trigger reset	—	Trigger reset	-
input/output	Output		ScanningOK/NG, contrastOK/NG Syncsignal of external lighting	_	ScanningOK/NG, contrastOK/NG Syncsignal of external lighting	-
Power unit	Rated voltage		5V			
	Power		Supplied from the higher-ranking equipment			
functions	Operating button		1 button (Magic key)			
	Batch reading of multiple codes		s Maximum 8			
	Image storage		Maximum 10			
norformonoo	Operating temperature		-20–50°C			
periormance	Protection rating		IP54			
Enclosure color (front)			White		Black	
Mass use of an exterior ingger, and is subject to			Approximately 120g	Approximately 150g	Approximately 120g	Approximately 150g

QB30 [Barcode] QB30 [2D code] QB31 [Barcode] QB31 [2D code] Scanning range and scanning depth Reading area 6 (Unit: mm

including sorting, extraction and conversion, is possible, reducing the burden involved in development of higher level systems.



Data collation and edit functions adopted

The scanner features a function for collating registered master data (up to 50 items)

with scanned code data, helping to build a system that checks for foreign articles

compatible with the simplified programming language "ADF Script," data editing,

prevents wrong labels from being affixed. Furthermore, since the scanner is

It supports operating temperature of -20-50°C and can be installed safely at a semi-outdoor entrance gate.

Product constituents

Main body set


- Operation guide
 User's manuale Option
- RS-232C D15P-to-D9S conversion cable* (CBQ3:RS2000/15-9-01 (2.0 m)
- AC adapter AD2-1005/3000* * Required when the RS-232C model is connected to an external device by using the D-sub9PIN.

Software

- USB driver 🛄
- [Active USB-COM port driver] Setup software
- [QB Setting] Keyboard emulation software
- [QR kbif]
- SQRC setup software [SQRC Setting]
 - You can download the items with this mark from our website for free.

Dimensions

HP.



Caution for safe use


Please carefully read the user's manual before using this product

External appearance and specification can be changed without notice
Contents stated in this catalog is data as of December 2014.

DENSO WAVE INCORPORATED



We Create [Value]² Unit 509, 5/F, Tower II, Cheung Sha Wan Plaza, 833 Cheung Sha Wan Road, Kowloon, Hong Kong Tel: (852) 2784 2868/ (852) 2788 3066 Fax: (852) 2319 2967 Email: sales@milliontech.com Website: www.milliontech.com



[QB31] Standard-range model allows scanning from a

